

Setting Up Early Model Receivers with a Quad LNBF

Quad LNBF:

These instructions assume you have already installed the DISH 500 and pointed it for the strongest possible signal strength for both the 110 and 119 locations.

To successfully connect the Quad LNBF to an older model receiver, such as a **Model 1000, 2000, 3000 or 4000**, do the following. **Note:** If your system has three satellites, you cannot use a Multi-Dish Switch SW21 to route the signal from the third satellite to the receiver. Instead, you must use a Multi-Switch SW64.

Important: There must be *no other receivers connected* to the Quad LNBF. If there are other receivers connected to the Quad LNBF you must disconnect them.

- 1) The receiver should power-up in the "Point Dish and Signal Strength Menu". If so, proceed to Step #4.
- 2) Turn on the Model 1000, 2000, 3000 or 4000. Press Menu on the remote.
- 3) Select **System Setup**, then **Installation**, then **Point Dish/Signal**.
- 4) Look to see if the number under **Transponder** in this screen is 01. If the number is not 01, move the highlight to the box under **Transponder**, and press the Up or Down arrow until you see the number 01.
- 5) Connect the Quad LNBF to the receiver.
- 6) Verify you have a signal, as indicated by the **signal strength** bar at the bottom of the screen. If you have a signal select **Save/Cancel**. If you do not have a signal, go to step #13.
- 7) An **Attention** screen will open asking if the mounting and positioning of your dish is complete with a "Locked" indication in the **Point Dish/Signal** screen. Select **Yes**.
- 8) After you select **Yes** you will see the message, "Vital program information will now be downloaded into your receiver. Do not disturb or unplug it for the next 5 minutes." Then the receiver begins taking the software upgrade.
- 9) When the software upgrade has finished your TV screen will go black for a few seconds, then display the message, "Acquiring Satellite Signal, Please Wait." A normal TV picture will appear.
- 10) Press Menu. Move the select **System Setup**, then **Installation**, then **Point Dish/Signal**.
- 11) Select the **Check Switch** option. An **Attention** screen will open. Select **Check**.
- 12) When **Check Switch** is complete you should see **Status: Satellite Reception Verified**.
- 13) If you *do not* have a signal with **Transponder** number 01, move the highlight to the box under **Transponder** and use the Up arrow key on the remote to change the **Transponder** number to 02. If you still *do not* have a signal, increment through the transponders until to have a signal.
- 14) Verify you now have a signal in the **signal strength** bar. Select **Save/Cancel**. Then do steps #7 - #13 to verify you have satellite reception.
- 15) Connect the rest of the receivers to the Quad LNBF following instructions in the User's Guide.



Nothing Else Compares.™